

## Q3000 SECURITY ALARM STARTER KIT

SMART HOME Q ALARM SERIES



### Product Features:

- Kit Includes:
  - IP Smart Alarm Hub x 1
  - DC-S1 Door/Window Contact x1
  - IR-S1L PIR Motion Detector x 1
- Advance Home Automation Functions
- Cloud Service
- Supports ZigBee Protocol
- Completely Wireless for easy installation
- Free Secure4Home app for your smartphone
- 40 zones of protection for your premises
- Program different zone types with specific device attributes, schedules, scenes
- Tamper detection to prevent unauthorized sabotage attempt
- Remotely control your security system & home appliances (accessories required)
- Get security alerts & push notifications
- Customizable and expandable
- Add PIR Cameras to create a total visual monitoring solution
- Pre-linked sensors
- Monitor energy consumption (PSM-S1 required)
- For indoor use only

### Technical Data:

- Protocol: ZigBee Home Automation 1.2
- Frequencies Available: 433 MHz/ 868MHz
- Power Supply: 9V 1A Switching Power
- Battery Backup: Ni-mh Rechargeable Battery 4.8V, 1100mAh
- Battery Backup Time: 15 hours
- Alarm Output: 95db @ 1M
- Range: 200-300M in open space
- Operation Temperature: -10°C to +45°C
- Operation Humidity: Up to 85% non-condensing
- Dimensions: 70.2mm x 70mm x 151mm